



Central support is NOT provided on E18, E24 or E30 enclosures

Two supporting brackets are used on E65, E65D and E82 enclosures

kVA	Model	H	W	D	A	B	C	F	G*
9-20	E18	24	18	16	19	15	13	13	-
21-75	E24	30	24	20	24.5	20.5	17	19	-
76-125	E30	34	30	24	28.5	26.5	21	21	-
126-225	E37	40	37	28	32.5	33.5	25	24	16.75
226-450	E45	48	45	30	34.5	41.5	27	27	20.75
451-700	E52	60	52	34	38.5	48.5	31	33	24.25
701-950	E52D	60	52	45	49.5	48.5	41	33	24.25
951-1500	E65	70	65	45	49.5	61.5	41	39	15.25
1501-3000	E65D	70	65	56	60.5	61.5	51	39	15.25
3001-5000	E82	91	82	70	74.5	78.5	64	52	23.5

* Distance between the mounting holes of side support brackets and their adjacent supporting brackets

NOTE:

- Dimensions are approximate to +/- 0.25"
- Mounting holes on all floor mount models are 0.5" x 0.75"
- Some of the options might increase the size of the enclosure for the same kVA rating (Please consult Synergy Energy Inc. for details)

		Synergy Energy Inc			
		DESCRIPTION: 3 Phase, Low Voltage Transformer Standard Enclosure Overall Dimensions			
DATE: 17-Sep-2008	SIZE: N/A	DIMENSIONS: INCHES	DWG. NO. LV-ISO-1000	REV 07	
REV. DATE: 23-Mar-2009	SCALE: None			SHEET: 1 OF 1	